

FRONT LOAD 2KW TV TRANSMITTER MOT 2000 FL

The 2KW TV transmitter **MOT 2000 FL** meets the strictest demands of the international Broadcasting according to CCIR and FCC specifications. It consists on the modulator transmitter MOT 15 FL and the S 2000 amplifier, which has 2KW and LDMOS technology. This transmitter covers the whole frequency range for III-IV-V bands.



MAIN ADVANTAGES

- Alarm and digitalized information system to control the following parameters: forward power, reflected power, service voltages, final-stage voltages and currents, video level, audio level, synchronism level, operation channel, offset and temperature.
- Protections against excess of forward power, SWR excess, over-voltage in power supply, over-current in amplifier and over-temperature.
- A digital telemetry output is included.
- A Notch BPF (Band Pass Filter) is included.

GENERAL CHARACTERISTICS

GENERAL	
CLASS	AB1
FREQUENCY RANGE	Bands III-IV-V
AVAILABLE STANDARDS	B, D, G, H, I, K, M, N
COOLING	Forced air fans
OPERATION TEMPERATURE	-10 to +45°C
STORAGE TEMPERATURE	-30 to +85°C
MAXIMUM RELATIVE HUMIDITY	90% without condensation
POWER SUPPLY	220VAC ±15%, 50/60Hz
CONSUMPTION	3.2KVA
PROTECTIONS	Excess of forward power, SWR, temperature, over current and modules voltage

broadcast your world

DIMENSIONS	1240x590x900cm
WEIGHT	144Kg

VIDEO	
INPUT CONNECTOR AND IMPEDANCE	BNC(F), 75Ω
INPUT LEVEL	1Vpp ±6dB
WHITE LIMITER	95%
2KT FACTOR	≤1.5%
AMPLITUDE/FREQUENCY RESPONSE	≤±0.5dB
CHROMINANCE/LUMINANCE INTERFERENCE	≤4%
ICPM	≤±3%
S/N RATIO (WEIGHTED)	≥60dB

AUDIO	
INPUT CONNECTOR AND IMPEDANCE	XLR(F), 600Ω-10KΩ (selectable)
INPUT LEVEL	0dBm ±8dB, 0.5dB steps
FREQUENCY RESPONSE	±0.5dB (typical ±0.2dB)
S/N RATIO (UNWEIGHTED)	≥65dB

OUTPUT	
NOMINAL OUTPUT POWER	2000Wps
OUTPUT IMPEDANCE	50Ω
UNEQUAL LOAD	2:1 max. ROE
IMD (-8 dB, -10dB, -16dB)	>-54dB (with nominal output power)
SPURIOUS	>-56dBc (with output filter)
OUTPUT FREQUENCY STABILITY	1ppm
OUTPUT CONNECTOR	EIA 7/8"
RF MONITOR CONNECTOR	BNC(F)

* The images and/or technical specifications are subject to change without previous notice.

broadcast your _ world